

PANASONIC KX-TGP500 & KX-TPA50 CORDLESS PHONE

Get to know your phone



Status Indicator
(Indicates Status of the unit and network)

Handset Locator button (ALL).
To page and connect handsets



Set up MessageBank®

- Dial **101** and follow the prompts to set up your voicemail greetings, etc.
- To listen to your messages enter **101** and follow the prompts to listen to your messages.

The **Message Light** will flash red if there are new messages.

Set up Phone Directory and save contacts

Each handset has its own phone directory and will need to be set up individually.

A phone directory can be created on the phone directly. You can import and export contacts from your PC using KX-TGP-500 web portal. Refer to your user guide for more details.

- To save a number in the directory press the **MENU** soft key and scroll to select the phonebook icon.

- Press the **ADD** soft key.
- Use the keypad to enter the **contact's number** and press **OK**.
- Press **SELECT** to create a distinctive **ringtone** for the contact or press **SAVE** to save the contact.
- Repeat the steps above to add another contact or press **OFF** button to exit.

Transfer calls (Blind or Supervised)

Transfer a call to another handset (with the same phone number)

To blind transfer (transfer without announcing the call prior to transfer)

- Press **MENU** during a call.
- Select **Intercom** to display all the Panasonic KX series handsets.
- Scroll and select the other party's handset.
- Press the **CALL** soft key.
- Press **OFF** when the party's phone rings to complete the transfer.

To supervise transfer (transfer with consultation to another party)

- Press **MENU** during a call.
- Select **Intercom** to display all the Panasonic KX series handsets.
- Scroll and select the other party's handset.
- Press the **CALL** soft key.
- Wait till the other party answers the call and announce the call.
- Press **OFF** to complete transfer.

Transfer a call to another handset (with a different phone number)

To blind transfer (transfer without announcing the call prior to transfer)

- Press **MENU** during a call.
- Scroll down to **Blind Transfer** and press **SELECT**.
- Enter the other party's phone number to complete blind transfer.
- Press **OFF** to complete transfer.

To supervise transfer (transfer with consultation to another party)

- Press **MENU** during a call.
- Scroll down to **Transfer** and press **SELECT**.
- Enter the other party's phone number and press **CALL**.
- To complete the transfer press **TRANS**.

Hold calls

- To put an active call on hold press the **HOLD** soft key, 'Line on hold' will display on the screen.
- To resume the call from hold press the **HOLD** soft key again.

Conference calls

- To create a conference call while on active call press the **MENU** soft key.
- Scroll down to **Conference** and press **SELECT**.
- Wait for the continuous dial tone and enter the new party's number. That handset will automatically dial.
- When the new party answers the call press the **CONF** soft key to connect all parties.
- If the new party does not answer, press **CANCEL** twice to return to the active call.

Call Forwarding and Call Waiting

There are 3 Call Forwarding options which can be set from your handset: Call Forward-Always, Call Forward-No Answer and Call Forward-Busy.

Call Forward-Always

1. Pick up handset and enter the assigned code ***72** and press the **CALL** button.
2. You'll be prompted to enter the phone number to which calls will be forwarded.
3. Hang up handset. Call Forward-Always is now activated.

To deactivate, repeat these steps using the code ***73**.

Call Forward-Busy

- Follow the Call Forwarding instructions above but use code ***90** to turn it on, and code ***91** to turn it off.

Call Forward-No answer

- Follow the Call Forwarding instructions above but use code ***92** to turn it on, and code ***93** to turn it off.

Call Waiting

- Lift the telephone handset and enter the assigned code ***43**. The Call Waiting feature is now turned on.
- To turn it off, repeat these steps using the code **#43**.